

B R O A D W A V E T E C H N O L O G I E S I N C .

MODEL 851 - 891 - FM0
IMPEDANCE MATCHING PAD

Frequency Range: DC - 500 MHz

Impedance: 25 Ohms nominal (Male side)
50 Ohms nominal (Female side)

Insertion Loss: 7.9 dB nominal

VSWR: 1.25:1 maximum (50 Ohms side)
2.00:1 nominal \pm 0.1
(25 Ohms side, as measured on 50 Ohm test system)

Input Power: 1 Watt average

Connectors: SMA Male/Female

Outline Drawing: MED - 0033

ECF #	Date	Rev.
Issue	10/11/06	0

Approved By: _____